

PATENT
450110-03706

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

APPLICATION FOR LETTERS PATENT

TITLE: MODIFYING MATERIAL

INVENTORS: Jason Charles PELLY, Stephen Mark
 KEATING

William S. Frommer
Registration No. 25,506
FROMMER LAWRENCE & HAUG LLP
745 Fifth Avenue
New York, New York 10151
Tel. (212) 588-0800

Modifying Material

BACKGROUND OF THE INVENTION

Field of the invention

5 the present invention relates to modifying material. Preferred embodiments of the invention relate to perceptible modification.

“Material” as used herein means information material which includes at least one or more of image material, audio material and data material. Image material is generic to still and moving images and includes video and other forms of information signals representing images.

Description of the Prior Art

10 It is known to watermark material. A watermark may be data embedded in material as a watermark. A watermark may be perceptible or hidden. Preferred embodiments of the present invention use perceptible watermarks.

15 It is also known to watermark an image by transforming the image from the spatial domain to a transform domain, e.g. to the wavelet domain and embed a watermark by changing the wavelet coefficients. The transform domain image with the watermark is then inverse transformed to the spatial domain. See for example “An image watermarking method based on the wavelet transform” by Hisashi Inoue, et al, IEEE, 0-7803-5467-2/99.

20 US Patent 5809139 (Girod et al) discloses the invisible watermarking of video material which is already compressed. Video which has been compressed by MPEG2 is entropy decoded and dequantised to obtain the DCT coefficients. A spread spectrum spatial domain watermark is transformed to the DCT domain and the transformed watermark added to the DCT coefficients of the transformed video. To maintain the bit
25 rate of the compressed video even with the addition of the watermark, various steps are taken. Only non-zero coefficients are modified. Also the number of bits of an encoded watermarked coefficient is compared against the number of bits of the coefficient prior to watermarking (plus any extra number of spare bits saved in previous coding operations). A control controls selection of the output between the
30 watermarked bitstream and the original unwatermarked bitstream. If an entropy encoded unwatermarked coefficient uses n_o bits and the watermarked entropy encoded

coefficient uses n_1 bits then a watermarked coefficient is output if $n_1 \leq n_0 + n_3$, where n_3 is the number of spare bits available for use. The watermark can be detected in a video decoder but it is not possible to restore the watermarked video to the original video by reversing the watermarking algorithm.

WO 99/10837 (Digimarc) discloses a method of watermarking a video image in which the image is compressed using for example MPEG2 and the DCT coefficients are modified to embed a watermark. The bit rate is preserved by maintaining a count that represents the amount the bit rate has been increased by the modifications to the coefficients less the amount the bit rate has been decreased by the modifications. If the cumulative change exceeds a positive or negative limit, then no further changes are made. The watermark can be detected in a video decoder but it is not possible to restore the watermarked video to the original video by reversing the watermarking algorithm.

Both US-A-5809139 and WO 99/10837 require means which monitor the bit rate and which stops embedding of a watermark if a specified limit is reached. For US-A -5809139 and WO 99/10837 that results in a random distribution of the watermark in an image. These proposals are aimed at irreversible imperceptible watermarks which embed data representing a message in the image.

It is known to compression encode material especially images. Also, if a modification is made to the material which adds data to the material, then the compression is usually less efficient. It is desirable to process compressed material, so as to produce modification of the material which is perceptible in the decompressed material, e.g. a visible modification in an image, with a minimal change to the number of bits representing the compressed material. Preferably it is desirable to modify material in a way which is easily applicable to both material which is already compressed and material which is to be compressed.

Summary of the Invention

According to one aspect of the present invention, there is provided a method of modifying material represented by information signals, comprising deriving digital representations of transform coefficients of the signals, and modifying and entropy encoding the digital representations, wherein at least some of the digital representations are modified by making pseudo random changes to them in accordance

with a substantially invertible algorithm, which changes do not substantially change the number of entropy encoded bits.

The term "not substantially change the number of entropy encoded bits " indicates that the number of bits may increase or decrease by a small amount relative to the number of bits of entropy encoded unmodified material and preferably the number of bits does not change.

"Pseudo random changes" may be applied by encrypting, transposing or permuting the bits of coefficients or groups of coefficients in accordance with pseudo random numbers derived from keys.

The method is easily applicable to both compressed and uncompressed material because it is applied to transformed coefficients . That is particularly advantageous for compressed material having a bit stream containing codes representing the coefficients because only extraction of the codes from the entropy encoded bitstream is needed before a modification is made. By modifying according to an invertible algorithm, the modification may be removed and the original material restored which is not possible in the prior proposals of Girod and Digimarc as described above.

Some embodiments of the invention apply a modification by transposing the values of representations with other values in accordance with a transposition algorithm. By suitably choosing the values which are transposed, the use of such transposition allows material to be modified without substantial change to the number of entropy encoded bits . Preferably, the number of bits does not increase. However in some circumstances, there may be a small increase or decrease in the number of bits.

In an embodiment of the invention which compresses material, by combining the application of the modification and compression, the compression does not damage the modification. Also by not substantially changing the number of bits used, the bandwidth (data rate) of the compressed and modified material is not substantially changed.

By using an invertible algorithm, the modification is removable and the original material restored provided that the modified material is not processed or otherwise altered in a way that irreversibly alters the changed compression encoded data.

The invention also provides apparatus for carrying out the method of said one aspect.

Another aspect of the invention provides a method of removing modifications applied to information signals representing material by the method of said one aspect, comprising deriving a bitstream representing entropy encoded digital representations of transform coefficients of the modified material, and extracting from the bitstream codes the coefficients and applying the inverse of the invertible algorithm thereto.

The invention also provides a computer program product arranged to implement the method of the said another aspect when run on a computer.

The invention also provides apparatus for carrying out the method of said another aspect.

It will be appreciated from the following description that the illustrative embodiments of the invention do not embed data representing a message in the material. The embodiments change selected coefficients or blocks of coefficients dependent on a bit map. The bit map may represent a pattern. However, the modifications made at the positions indicated by the bit map do not represent intelligible data.

BRIEF DESCRIPTION OF THE DRAWINGS

The above and other objects, features and advantages of the invention will be apparent from the following detailed description of illustrative embodiments which is to be read in connection with the accompanying drawings, in which:

Figure 1 is a schematic block diagram of a video signal processor embodying the invention;

Figure 2 explains how an image is changed by the processing of the system of Figure 1;

Figures 3A and 3B schematically illustrate the contents of frame stores of the system of Figure 1;

Figure 4 is a flow chart illustrating the processing of DC transform coefficients;

Figure 5 illustrates the encoding of DC coefficient values;

Figures 6, 7, 8 and 9 are flow charts illustrating the processing of AC transform coefficients;

Figure 10 is a schematic diagram of a smart card;

Figure 11 is a schematic block diagram of a decoder embodying the invention;

Figure 12 is a schematic flow diagram corresponding to Figure 6 illustrating the restoration of AC coefficient values;

Figure 13 an example of a watermarked image produced in accordance with the invention; and

Figure 14 is a schematic flow diagram of an illustrative system in accordance with the invention for processing video from a source of compressed video.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Overview

The embodiments of the invention described herein apply modifications, herein referred to as a watermark, to an image. Figure 13 is an example of a watermarked image produced by an embodiment of the invention. As will become apparent from the following illustrative description, although the overall effect of the modifications shown in Figure 13 is a pattern of an intelligible shape (SONY), the modifications themselves do not represent data. Furthermore the pattern itself need not be intelligible

Encoder, Figure 1.

Figure 1 is an example of an encoder. The encoder of Figure 1 is for example a high definition camera/recorder which includes an image compression system. The encoder comprises a source 1 of a color analogue image and an analogue to digital converter and processor 2 which samples the image according to the well known 4:2:2 format. As shown in Figure 2, a frame of the luminance component image has 1920 samples in each of 1080 lines. The processor 2 filters the image and outputs a 3:1:1 subsampled image. The luminance (Y) component has 1440 digital samples on each of 1080 lines as shown in Figure 2b. A demultiplexer 3 separates odd and even samples onto separate odd and even channels. Thus as shown in Figure 2c, a frame of even Y samples has 720 samples on each of 1080 lines. A frame of odd samples is the same.

In this example, the encoder is part of a camera/recorder. Blocks of odd and even samples corresponding to DCT blocks described below are shuffled according to

a known shuffling algorithm in processors 4o and 4e. The odd and even samples are recorded on separate tracks of a video tape in known manner. Shuffling is performed to minimise the effect of tape defects on an image reproduced from the tape, as is well known in the art. Shuffling is also used to improve shuttle playback. Shuffling is not essential to the invention.

Each frame of odd and even shuffled digital samples, represents a spatial domain image. The odd and even frames are transformed to the DCT domain by respective transformers 5o and 5e. As shown in Figure 2d, each transformed frame of odd or even Y samples comprises 90 by 135 DCT blocks, each block comprising 8 by 8 DCT coefficients as shown in Figure 2e. Each DCT block has one DC coefficient denoted DC in Figure 2e and 63 AC coefficients, one example of which is denoted by AC in figure 2e.

The DCT coefficients are quantised in quantisers 6o and 6e, the quantisation being controlled by a control value Q in known manner. In the absence of watermarking, the odd and even frames of quantised DCT coefficients are entropy encoded in entropy encoders 8o and 8e in known manner. The entropy encoding in this example includes encoding using Huffman encoding. The entropy encoded quantised coefficients are in this example recorded in known manner on a tape; that is not shown in Figure 1. Recording could be on other recording media, for example discs.

Modifying the quantised DCT Coefficients to apply the watermark.

The odd and even channels of the encoder have change processors 7o and 7e which modify the quantised luminance (Y) DCT coefficients to apply the watermark. The following description refers to only one, 7, of the processors. The other processor operates in the same way. The following assumes by way of example that the quantised DCT coefficients are represented by n bit numbers where n is in the range 8 to 14; that is DC coefficients may have 8 to 14 bits; and AC coefficients have 14 bits. For ease of description the following refers to n bit numbers.

Defining the form of the watermark.

Referring to Figure 3A and to Figure 13, the form of the watermark is defined by a bit map stored in a frame store 9a of the change processor 7. The bit map contains data selecting the DCT blocks in which coefficients are to be changed to apply the

watermark. For example a bit value 0 in a location on the store 9A indicates the a DCT block in a corresponding location in the image is not to be changed whereas bit value 1 selects the block for change.

In a preferred embodiment there are two such stores. One selects DCT blocks in which AC coefficients are to be changed and the other selects blocks in which the DC coefficient is to be changed. Most preferably the selections made by the two stores are independent. The stores 9 are referred to hereinafter as template stores. The following description assumes that DC coefficients are processed differently to AC coefficients. In an alternative embodiment only DC coefficients are changed to apply a watermark. In a further embodiment only AC coefficients are changed to apply a watermark.

For ease of explanation and ease of illustration, the bit maps shown in Figures 3A and 3B assume that the digital samples have not been shuffled.

Processing DC coefficients, Figures 4 and 5.

Referring to Figure 3B, the change processor 7 has a change function store 9B which stores a change value C for the DC coefficient of each DCT block selected by the bit map in the DC template store 9A.

Referring to Figure 4, the change value C is calculated by the processor 7 in the following way.

S1. The DC template of Figure 3A is created. Different levels L may be specified for different parts of the watermark as illustrated in Figure 3A. L is defined by a 8 bit number and so it has values in the range 0 to 255. In Figure 3A L has values 5 and 127 by way of example for different parts of the template. The levels may be stored in the DC template.

S2. Pseudo random numbers RN1 are generated based on a first key, Key1. The numbers RN1 are constrained within a predetermined range $\min \leq \text{RN1} \leq \max$ for example $100 \leq \text{RN1} \leq 1000$. A new random number is generated for each DCT block which is to have its DC value changed (as indicated by the DC template).

S3. The change values C are calculated according to

$$C = (L/M) \cdot \text{RN1}$$

where M is the maximum value which L can take: in this example $M = 255$. The change values are stored in the change store 9B.

It will be recalled that the same process occurs in both the even sample change processor 7e and the odd one 7o. However, the quantisation scales applied to the odd and even channels may be different. Thus different changes could be applied to even and odd samples. That would produce a striped image. If a striped image is not wanted, step S4 is implemented but step S4 is not essential to the invention.

Steps S1 to S3 may take place before an image is compressed and watermarked. The adjustment of the change values C by step S4 takes place during compression processing because it depends on the particular quantisation scales applied to the odd and even samples during such processing.

S4. The digital change value C is adjusted as follows to produce an adjusted value C^{\wedge} where

$C^{\wedge} = C \gg (13 - B)$, where B is the number of bits needed to specify the DC magnitude after quantisation, and \gg means right shift in this case (by $(13-B)$ bits).

That occurs in both the odd and even channels and results in approximately the same change being applied in both channels. There may be different values for B on the odd and even tracks B_o and B_e . 13 is the number of magnitude bits of a signed 14 bit number, the extra bit being a sign bit.

S5. The quantised DC coefficients are then adjusted by the values C^{\wedge} according to an invertible algorithm. The quantised DC coefficients each have n bits, where n may differ from DC coefficient to DC coefficient. The change is such that for any coefficient the number n of bits does not change.

Figure 5 illustrates a currently preferred algorithm (algorithm 1) for changing the DC coefficient values. Assume by way of example that $C^{\wedge}=10$ and $n=8$ bits so the coefficient has a value in the range -128 to $+127$. Starting at -128 , the bottom of the range, the range of values is divided into sections each of range 2×10 . Sections -128 to -109 ; -108 to -89 ; and so on to $+111$ are shown. The whole range does not divide into an integer number of sections each of range 2×10 . Thus there is a top section of $+112$ to $+127$.

The algorithm operates by swapping a value in the top half of a section with a value in the bottom half. Thus values -128 to -119 swap with values -118 to -109 . Thus if a coefficient has an original value -118 , before adjustment by $C^{\wedge}=10$, it is

replaced by -128 after adjustment by C^\wedge . As another example if an original value is -107 , it becomes -97 after adjustment. In the top section $+112$ to $+127$ the same process occurs but the half sections are $+112$ to $+119$ and $+120$ to $+127$ and the swapping is as shown in the Figure.

The example given divides the whole range into sections beginning at the bottom (-128) of the range. The division may take place starting at the top ($+127$) of the range. In a preferred embodiment, the division begins at the top or bottom according to the value of a pseudo randomly generated bit PRB generated based on a key, Key2. PRB may pseudo randomly change for every DC coefficient. The values of the bit PRB are preferably stored in the change store together with C.

When a quantised DC coefficient is produced by the quantiser Q, the processor 7 determines from the change store the value of C applicable to the coefficient and the value of PRB. The processor 7 adjusts the value of C to C^\wedge . The value of that coefficient is adjusted according to C^\wedge and the algorithm. Using the example of Figure 5, if the coefficient has an original value of -96 it is replaced by -106 .

In summary, the n bit numbers representing the coefficients are members of a set and a said number is modified by transposing it with another member of the set chosen according to the invertible algorithm. As shown in Figure 5, if a number N1 is to be changed by an amount X it is transposed with another member N2 of the set where $|N1-N2| = X$, except at one end of the range where only a change of less than X is possible.

It will be appreciated from the foregoing that the number of bits is not changed.

S17, S18. The foregoing description may apply to a single frame of a still image. For video with many frames in a clip, the change values C and PRB stored in the store 9B are applied to all the frames in the clip. However in addition, to increase security, a small pseudo random variation RN2 based on a key Key5 is added to the change values C of each frame. The small variation is chosen so that the number of bits does not increase. At step S3, the change store is established and remains fixed for the clip. The small variation is a small pseudo random number e.g. –

$50 \leq RN2 \leq 50$, and it is added to C just prior to step S4. Each C gets a new value of RN2. The PRBS generating RN2 is *not* reset every frame, so different frames have different sequences of RN2.

Processing AC coefficients, Figures 6 to 9.

S6. An AC template is created. The bit map in the AC template selects the DCT blocks in which AC coefficients are to be changed.

- 5 S61. If an AC coefficient is to be changed its value is tested; if it equals zero, no change is made to its value; otherwise it is changed.

S7, S8 and S9. The AC coefficients in the selected blocks are compared with a threshold T_s . If the magnitude of a coefficient is below T_s then its sign may be changed. If the value is greater than T_s the sign must not change. Although it is not essential to the principle of the invention to prevent a sign change in an AC
10 coefficient, it has been found that a sign change for large valued coefficients creates a watermark which is unpleasant.

S10. The numbers representing the AC coefficients are changed according to an invertible algorithm and a key, Key3.

- Figure 7 illustrates one example of the invertible algorithm (algorithm 2). The
15 algorithm operates on quantised AC coefficients prior to entropy encoding.

Referring to Table 1, which is a Huffman encoding table and which is attached to the end of this description, the coefficient values are represented by a variable length code VLC and a fixed length code FLC. The VLC specifies which of the groups an AC coefficient lies in. The FLC is an index which indicates which value
20 in the group is equal to the AC coefficient

Step S11 determines which group the coefficient lies in.

Step S111 determines the index of the coefficient in the group.

- In step S12 the fixed length code of AC coefficients in blocks selected by the AC template is changed by adding to it a pseudo random number RN3 based on a key,
25 Key3. To ensure that the number of bits does not change the sum "wraps round". For example if the fixed length code is 110 and the RN3 is 010 then the sum wraps round to 000 rather than 1000. If no change of sign is to occur as indicated by steps S7 and S9, then the wrap around is performed so as to preserve the sign of the coefficient.

- In Step S121 the coefficient value is set to the value pointed to by the new
30 index.

Figure 8 illustrates another example of the invertible algorithm. The algorithm operates in the same way as Figure 7 except step S12 is replaced by step S13.

In step S13 the fixed length code is encrypted according to an invertible encryption code and a key Key3'. The number of bits is not changed.

Figures 7 and 8 are concerned with changing the value of a coefficient to another value in the same magnitude group.

5 Figure 9 illustrates an invertible algorithm for changing the order of coefficients. This may be used in addition to the algorithm of Figure 7 or 8.

S14. The number of bits to entropy encode a sequence of AC coefficients is determined.

10 S15. The change processor 7 attempts to find a permutation of the order of coefficients which does not change the number of bits produced by entropy encoding.

S16. If a permutation is found, then a decision is made to either change the order or not change the order. The decision depends on the value of a pseudo random number PRB2 defined by a key Key4. In this example the number may have only one bit.

15 In a modification of step S15, the change processor finds more than one permutation of the order of coefficients which does not change the number of bits produced by entropy encoding. The permutations, including the original order of coefficients are numbered to identify them. In step S16, one of the permutations is selected on the basis of the pseudo random number PRB2.

20 In a modification of the process, the AC coefficients in a block are selected for change. In such a block not all coefficients are changed. The selection may be a preset fixed selection or a selection which varies. The selection may be pseudo random based on a key.

Creating watermarked spatial domain images.

25 The compressed watermarked image may be stored in compressed form on the tape. To view the image it must be decompressed.

Referring to Figure 11, the Figure shows only the "odd" channel of the decoder. The "even" channel is similar. The compressed image is entropy decoded (18), dequantised (16) and inverse transformed (15). The resulting spatial domain samples are unshuffled (14) and the odd and even samples remultiplexed (13) to produce a watermarked spatial domain image. The remultiplexed samples are inverse filtered (12) to produce a 4:2:2 image. Figure 13 is an example of such an image.

It will be noted that a watermark removal processor 17 of Figure 11 is bypassed by bypass 19 for the purpose of viewing the watermarked image.

Removing the Watermark.

Data Carrier. Figure 10

In order to remove the watermark, the decoder must have the following removal data:

The AC and DC templates, levels L, the maximum and minimum values for RN1, the keys 1, 2, 3, 4 and 5 for generating the pseudo random numbers and bits, the algorithms 1 and 2 and the threshold Ts. The keys are generated in the encoder and are not predetermined.

In the currently preferred embodiment, the removal data is stored in a data carrier preferably securely. Most preferably the carrier is a smart card SC. The encoder has an interface via which the change processors 7e and 7o download the removal data into the smart card SC.

The removal processors 17 of the decoder have a similar interface for receiving the removal data from the smart card SC.

Removal of changes from the DC coefficients

Referring to Figures 4 and 11, the removal processor 17 downloads the DC template, Key1 and the limits to the range of RN1 from the smart card SC.

- S1. The templates and levels L are available from the smart card.
- S2. The removal processor 17 recreates, from the Key1 and the limits, the pseudo random numbers RN1.
- S3. The changes C are recalculated from the template, L and RN1. and stored in a change store as shown in Figure 3B.
- S4. The adjusted change values C^{\wedge} are calculated from the stored values of C..
- S5. The DC coefficients are restored to their original values by inverting the algorithm with reference to the pseudo random bits PRB1 regenerated from Key2.
- S17, S18. For video clips, RN2 is regenerated from Key5 and subtracted from C.

Restoring AC coefficients

Referring to Figure 12:

S6'. The AC template is downloaded from the smart card.

S61'. If an AC coefficient is to be changed, the coefficient is tested to determine whether or not it has a value of zero. If the value is non zero then it is subject to change at the encoder and thus also at the decoder.

5 S10'. The AC coefficients are restored to their original values by inverting the algorithm with reference to Key 3.

S7' to S9'. The coefficient values are compared with Ts downloaded from the smart card. That allows the processor to determine which coefficients have a sign change.

10 Referring to Figures 7 and 8, steps S11 and S111 are followed as in the process of changing the coefficients.

Referring to Figure 7, at S12 RN3 is regenerated from Key3 and is subtracted from the index.

Referring to Figure 8, at S13, the encryption is reversed using Key3'.

15 Referring to Figure 9:-

S14. The number of bits to entropy encode a sequence is determined.

S15. The change processor 7 attempts to find a permutation of the order of coefficients which does not change the number of bits required to be entropy encoded.

20 S16. If such a permutation is found, then it is possible that in the change process a decision was made to change the order. The decision depends on the value of the pseudo random number PRB2 defined by Key4.

PRB2 indicates whether the sequence has been changed. If it has, the change is inverted.

Security

25 The algorithms used to apply the watermark may be common to many different users. Security is provided by:

- a) the keys Key1, 2, 3, 4 and 5 which are chosen and generated by the users;
- b) the levels L which are chosen by the users; and
- c) the limits on RN1 which are chosen by the users.

30 The sign change threshold may provide some security because it is selectable by the users.

The DC and AC templates are not secure if a visible watermark is applied to an image because the template is at least partially visible in the image.

Smart cards are physically and logically designed to store data securely.

Related system and method

- 5 The method and apparatus described herein may be used with the method and system disclosed in copending application 0029851.3, attorney file P/10406, I-00-153 the disclosure of which is incorporated herein by reference.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
219

Adding a watermark to video which has previously been compressed.

The foregoing description applies a watermark to video during the process of compressing the material. However material is available which is compressed but does not have a watermark but it is desirable to add a watermark to it. Figure 14 is a

5 schematic flow diagram of an illustrative system in accordance with the invention for processing video from a source 71 of compressed video. The source 71 may be a video tape player or player and recorder, a disc player or player and recorder, a server or any other source. For ease of explanation, and consistency with the foregoing description, it is assumed that the video has been compressed by a system as shown in Figure 1 but
10 omitting the change processors 7e and 7o. The compressed video thus is not watermarked.

In this example, the compressed video comprises data encoded according to the coding set out in Table 1 at the end of this description. The data is analysed (72) to:

- 15 1) extract the individual codes. The non-zero AC coefficients each have the form <VLC> <FLC> as shown in Table 1. DC coefficients are encoded as raw data in n bits;
- 2) determine the positions in the bit map of Figure 3 which the codes represent; and
- 3) determine other information such as quantisation level of DC coefficients.

20 The entropy encoded bit stream is a stream of data organised in known manner and from which it is possible to identify the codes in known manner. The ordering of the codes is in a known relationship to the image positions.

A comparator 74 compares the code positions with the bit map stored in a template store 73 to determine whether the code needs to be changed or not.

25 If a code needs to be changed then step 75 determines whether the code represents an AC or DC coefficient. If the code represents an AC coefficient, then one of the methods of Figures 6 to 9 as described above is used. If the code represents a DC coefficient, then the method of Figure 5 as described above is used. .

30 All the codes, that is both the changed and unchanged codes are stored in a store 76, for example a video tape recorder. The unchanged codes are fed to the store 76 via a delay 77 which compensates for the processing delay of the changed codes so that the order of the codes is unchanged in the examples of Figures 7 and 8.

If a compressed bit stream is required then the bitstream is stored in a store 76 without further processing. If an uncompressed bit stream is required the bitstream is decompressed and then stored.

This process for embedding a watermark in video which is already compressed is advantageous because it does not require the video to be decompressed: that is it does not need to be dequantised and does not need an inverse transform operation.

Removing the watermark

The watermark may be removed and the original video restored by the inverse of the method shown in Figure 14. The data from a source 71 is analysed (72) to:

- a) extract the individual codes. The non-zero AC coefficients each have the form <VLC> <FLC> as shown in Table 1. DC coefficients are encoded as raw data in n bits;
- b) determine the positions in the bit map of Figure 3 which the codes represent; and
- c) determine other information such as quantisation level of DC coefficients.

The entropy encoded bit stream is a stream of data organised in known manner and from which it is possible to identify the codes in known manner. The ordering of the codes is in a known relationship to the image positions.

A comparator 74 compares the code positions with the bit map stored in a template store 73 to determine whether the code was changed or not during embedding

If a code was changed then step 75 determines whether the code represents an AC or DC coefficient. If the code represents an AC coefficient, then one of the methods of Figures 12 and 7 to 9 as described above is used to remove the modification. If the code represents a DC coefficient, then the method of Figure 5 as described above is used for removal..

All the codes, that is both the changed and unchanged codes are stored in a store 76, for example a video tape recorder. The unchanged codes are fed to the store 76 via a delay 77 which compensates for the processing delay of the changed codes so that the order of the codes is unchanged in the examples of Figures 7 and 8.

If a compressed bit stream is required then the bitstream is stored in a store 76 without further processing. If an uncompressed bit stream is required the bitstream is decompressed and then stored.

Modifications

Although the invention has been described by way of example with reference to information signals recorded on tape, any other suitable storage media may be used, for example, disc stores and solid state stores.

In the examples of Figures 1 to 14, the video is compressed according to one particular example of a compression system. The invention is not limited to that one example. The invention may be applied to many other compression systems including HDCAM, MPEG, JPEG, Motion JPEG, and DV.

In the examples of Figures 1 to 13, the watermark is fixed in image space and, except for the minor variation provided in video by RN2 in the example of Figure 4, does not vary in time. The invention is not limited to that. The watermark may vary in image space with time in a video sequence. One way of doing that is to provide a plurality of bit maps (also referred to herein as templates) which define watermarks in different positions and to use the bit maps in succession. Also the different bit maps may define different levels L: see Figure 3B and step S1 of Figure 4, so that the watermark has a varying level of visibility with time.

JPEG is mentioned above as an example of a compression system to which the invention may be applied. The examples of the invention aim to embed a watermark in compressed digital information signals without increasing the number of bits used to represent the compressed information signals as compared to the same compressed information signals without the embedded watermark. If the examples of the invention are applied to JPEG, there may be a small change in the number of bits. This is because JPEG uses predetermined control characters which may be accidentally produced by application of the examples of the present invention. If this happens the JPEG algorithm automatically adds an extra byte to avoid this problem. The result may be to increase or decrease the number of bits. Also, to make the modification more visible, a small increase in the number of bits may be acceptable, especially when stored on discs and other non-tape formats.

Although the foregoing description refers to video, the invention is not limited to video. It may be applied to audio, still images and other information signals.

Although illustrative embodiments of the invention have been described in detail herein with reference to the accompanying drawings, it is to be understood that the invention is not limited to those precise embodiments, and that various changes and

modifications can be effected therein by one skilled in the art without departing from the scope and spirit of the invention as defined by the appended claims.

100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200

Table 1.

VLC Group	Number of EOB Bits	Description
0	0	EOB code
1	1	$(1)^*0$, +/- 1
2	2	$(2 \text{ to } 3)^*0$, +/- 1
3	3	$(4 \text{ to } 7)^*0$, +/- 1
4	4	$(8 \text{ to } 15)^*0$, +/- 1
5	5	$(16 \text{ to } 31)^*0$, +/- 1
6	6	$(32 \text{ to } 63)^*0$, +/- 1
7	0	$(1)^*0$
8	1	$(2 \text{ to } 3)^*0$
9	2	$(4 \text{ to } 7)^*0$
10	3	$(8 \text{ to } 15)^*0$
11	4	$(16 \text{ to } 31)^*0$
12	5	$(32 \text{ to } 63)^*0$
13	1	+/- 1
14	2	-3 to -2, +2 to +3
15	3	-7 to -4, +4 to +7
16	4	-15 to -8, +8 to +15
17	5	-31 to -16, +16 to +31
18	6	-63 to -32, +32 to +63
19	7	-127 to -64, +64 to +127
20	8	-255 to -128, +128 to +255
21	14	-8192 to -256, +256 to +8191

In this table:

1. $(x \text{ to } y)^*0$, +/- 1 means from "x" to "y" zero value coefficients followed by a coefficient of +1 or -1
2. $(x \text{ to } y)^*0$ means from "x" to "y" zero value coefficients.